

5250/3270 Keyboard Map

for 28-Key MC3000

Booting Procedures

Boot Type	Procedure
Warm Boot	Selected via Start Menu
Cold Boot	Hold Power button for 15 Seconds

Local Terminal Functions

Local Function	Key Sequence
Program Information	<Func><Ctrl>*<P>
Diagnostics	<Func><Ctrl>*<D>
Keyclicks On/Off	<Func><Ctrl>*<K>
Quiet Mode On/Off	<Func><Ctrl>*<Q>
Terminal Configuration	<Func><Ctrl>*<C>
Host Profiles	<Func><Ctrl>*<R>
Message Recall	<Func><Ctrl>*<M>
Free Cursor Mode	<Func><Ctrl>*<F>
Close Session	<Func><Ctrl>*<T>
Previous Session	<Ctrl><Left>
Next Session	<Ctrl><Right>
Caps Lock	N/A
View Mode On/Off	<Func><Ctrl>*<Z>
Scroll Left	<Func><Ctrl><Left Arrow>
Scroll Right	<Func><Ctrl><Right Arrow>
Scroll Up	<Func><Ctrl><Up Arrow>
Scroll Down	<Func><Ctrl><Down Arrow>

*Alpha Mode

5250/3270 Keyboard Map

for 28-Key MC3000

5250 Emulation Keys

5250 Key	Key Sequence
Attention	<Ctrl>*<A>
Backspace	<BKSP>
Back Tab	<Shift><Func><Right Arrow>
Clear	<Func><Ctrl><BKSP>
Delete	<Shift><BKSP>
Dup	<Ctrl><4>
Enter (Send)	<Ctrl><Enter>
Erase Input	<Ctrl>*<E>
Field Exit	<Enter>
Field Minus	<Shift><Enter>
Help	<Ctrl>*<G>
Home	<Ctrl><5>
Insert	<Ctrl><9>
Print	<Ctrl>*<P>
Reset	<Ctrl>*<R>
Roll Up	<Shift><Up>
Roll Down	<Shift><Down>
System Request	<Ctrl>*<S>
Tab	<Func><Right Arrow>
Left Arrow	<Left Arrow>
Right Arrow	<Right Arrow>
Up Arrow	<Up Arrow>
Down Arrow	<Down Arrow>

*Alpha Mode

5250 Key	Key Sequence
F1	<Func><1>
F2	<Func><2>
F3	<Func><3>
F4	<Func><4>
F5	<Func><5>
F6	<Func><6>
F7	<Func><7>
F8	<Func><8>
F9	<Func><9>
F10	<Func><0>
F11	<Shift><Func><1>
F12	<Shift><Func><2>
F13	<Shift><Func><3>
F14	<Shift><Func><4>
F15	<Shift><Func><5>
F16	<Shift><Func><6>
F17	<Shift><Func><7>
F18	<Shift><Func><8>
F19	<Shift><Func><9>
F20	<Shift><Func><0>
F21	<Ctrl><Func><1>
F22	<Ctrl><Func><2>
F23	<Ctrl><Func><3>
F24	<Ctrl><Func><4>

5250/3270 Keyboard Map

for 28-Key MC3000

3270 Emulation Keys

3270 Key	Key Sequence
Attention	<Ctrl>*<A>
Backspace	<BKSP>
Back Tab	<Shift><Func><Right Arrow>
Clear	<Esc>
Clear EOF	<Ctrl>*<O>
Delete	<Shift><BKSP>
Dup	<Ctrl><4>
Enter	<Enter>
Erase Input	<Ctrl>*<E>
Field Mark	<Ctrl>*<F>
Home	<Ctrl><5>
Insert	<Ctrl><9>
New Line	<Ctrl>*<N>
Reset	<Ctrl>*<R>
System Request	<Ctrl>*<S>
Tab	<Func><Right Arrow>
Left Arrow	<Left Arrow>
Right Arrow	<Right Arrow>
Up Arrow	<Up Arrow>
Down Arrow	<Down Arrow>
PA1	<Ctrl><1>
PA2	<Ctrl><2>
PA3	<Ctrl><3>

*Alpha Mode

3270 Key	Key Sequence
F1	<Func><1>
F2	<Func><2>
F3	<Func><3>
F4	<Func><4>
F5	<Func><5>
F6	<Func><6>
F7	<Func><7>
F8	<Func><8>
F9	<Func><9>
F10	<Func><0>
F11	<Shift><Func><1>
F12	<Shift><Func><2>
F13	<Shift><Func><3>
F14	<Shift><Func><4>
F15	<Shift><Func><5>
F16	<Shift><Func><6>
F17	<Shift><Func><7>
F18	<Shift><Func><8>
F19	<Shift><Func><9>
F20	<Shift><Func><0>
F21	<Ctrl><Func><1>
F22	<Ctrl><Func><2>
F23	<Ctrl><Func><3>
F24	<Ctrl><Func><4>

5250/3270 Keyboard Map

for 28-Key MC3000

5250/3270 Character Map

Char	Key Sequence
Space	<Space>
!	<Shift><1>
“	N/A
#	<Shift><3>
\$	<Shift><4>
%	<Shift><5>
&	<Shift><7>
'	N/A
(	<Shift><9>
)	<Shift><0>
*	<Shift><8>
+	N/A
,	N/A
-	N/A
.	<.>
/	N/A
0	<0>
1	<1>
2	<2>
3	<3>
4	<4>
5	<5>
6	<6>
7	<7>
8	<8>
9	<9>
:	N/A
;	N/A
<	N/A
=	N/A
>	<Shift><.>
?	N/A
@	<Shift><2>

*Alpha Mode

Char	Key Sequence
A	*<A>
B	*
C	*<C>
D	*<D>
E	*<E>
F	*<F>
G	*<G>
H	*<H>
I	*<I>
J	*<J>
K	*<K>
L	*<L>
M	*<M>
N	*<N>
O	*<O>
P	*<P>
Q	*<Q>
R	*<R>
S	*<S>
T	*<T>
U	*<U>
V	*<V>
W	*<W>
X	*<X>
Y	*<Y>
Z	*<Z>
[	N/A
\	N/A
]	N/A
^	<Shift><6>
~	N/A
`	N/A

Char	Key Sequence
a	<Shift>*<A>
b	<Shift>*
c	<Shift>*<C>
d	<Shift>*<D>
e	<Shift>*<E>
f	<Shift>*<F>
g	<Shift>*<G>
h	<Shift>*<H>
i	<Shift>*<I>
j	<Shift>*<J>
k	<Shift>*<K>
l	<Shift>*<L>
m	<Shift>*<M>
n	<Shift>*<N>
o	<Shift>*<O>
p	<Shift>*<P>
q	<Shift>*<Q>
r	<Shift>*<R>
s	<Shift>*<S>
t	<Shift>*<T>
u	<Shift>*<U>
v	<Shift>*<V>
w	<Shift>*<W>
x	<Shift>*<X>
y	<Shift>*<Y>
z	<Shift>*<Z>
{	N/A
	N/A
}	N/A
~	N/A
¢ ¹	N/A
¬ ¹	N/A
¡ ¹	N/A

¹ Only in 5250 mode.