

# 5250/3270 Keyboard Map

## for 38-Key MC3000

### Booting Procedures

| Boot Type | Procedure                        |
|-----------|----------------------------------|
| Warm Boot | Selected via Start Menu          |
| Cold Boot | Hold Power button for 15 Seconds |

### Local Terminal Functions

| Local Function         | Key Sequence        |
|------------------------|---------------------|
| Program Information    | <Func><Ctrl>*<P>    |
| Diagnostics            | <Func><Ctrl>*<D>    |
| Keyclicks On/Off       | <Func><Ctrl>*<K>    |
| Quiet Mode On/Off      | <Func><Ctrl>*<Q>    |
| Terminal Configuration | <Func><Ctrl>*<C>    |
| Host Profiles          | <Func><Ctrl>*<R>    |
| Message Recall         | <Func><Ctrl>*<M>    |
| Free Cursor Mode       | <Func><Ctrl>*<F>    |
| Close Session          | <Func><Ctrl>*<T>    |
| Previous Session       | <Ctrl><F9>          |
| Next Session           | <Ctrl><F10>         |
| Caps Lock              | N/A                 |
| View Mode On/Off       | <Func><Ctrl>*<Z>    |
| Scroll Left            | <Ctrl><Left Arrow>  |
| Scroll Right           | <Ctrl><Right Arrow> |
| Scroll Up              | <Ctrl><Up Arrow>    |
| Scroll Down            | <Ctrl><Down Arrow>  |

\*Alpha Mode

# 5250/3270 Keyboard Map

## for 38-Key MC3000

### 5250 Emulation Keys

| 5250 Key       | Key Sequence               |
|----------------|----------------------------|
| Attention      | <Ctrl><7>                  |
| Backspace      | <BKSP>                     |
| Back Tab       | <Shift><Func><Right Arrow> |
| Clear          | <Func><Ctrl><BKSP>         |
| Delete         | <Ctrl><BKSP>               |
| Dup            | <Ctrl><2>                  |
| Enter (Send)   | <Ctrl><Enter>              |
| Erase Input    | <Ctrl><1>                  |
| Field Exit     | <Enter>                    |
| Field Minus    | <Ctrl>*<F>                 |
| Help           | <Ctrl><4>                  |
| Home           | <Ctrl><8>                  |
| Insert         | <Ctrl><9>                  |
| Print          | <Ctrl><, >                 |
| Reset          | <Ctrl><, >                 |
| Roll Up        | <Ctrl><6>                  |
| Roll Down      | <Ctrl><3>                  |
| System Request | <Ctrl><5>                  |
| Tab            | <Func><Right Arrow>        |
| Left Arrow     | <Left Arrow>               |
| Right Arrow    | <Right Arrow>              |
| Up Arrow       | <Up Arrow>                 |
| Down Arrow     | <Down Arrow>               |
|                |                            |

\*Alpha Mode

| 5250 Key | Key Sequence |
|----------|--------------|
| F1       | <F1>         |
| F2       | <F2>         |
| F3       | <F3>         |
| F4       | <F4>         |
| F5       | <F5>         |
| F6       | <F6>         |
| F7       | <F7>         |
| F8       | <F8>         |
| F9       | <F9>         |
| F10      | <F10>        |
| F11      | <Shift><F1>  |
| F12      | <Shift><F2>  |
| F13      | <Shift><F3>  |
| F14      | <Shift><F4>  |
| F15      | <Shift><F5>  |
| F16      | <Shift><F6>  |
| F17      | <Shift><F7>  |
| F18      | <Shift><F8>  |
| F19      | <Shift><F9>  |
| F20      | <Shift><F10> |
| F21      | <Ctrl><F1>   |
| F22      | <Ctrl><F2>   |
| F23      | <Ctrl><F3>   |
| F24      | <Ctrl><F4>   |

# 5250/3270 Keyboard Map

## for 38-Key MC3000

### 3270 Emulation Keys

| 3270 Key       | Key Sequence               |
|----------------|----------------------------|
| Attention      | <Ctrl><7>                  |
| Backspace      | <BKSP>                     |
| Back Tab       | <Shift><Func><Right Arrow> |
| Clear          | <Esc>                      |
| Clear EOF      | <Ctrl><0>                  |
| Delete         | <Ctrl><BKSP>               |
| Dup            | <Ctrl><2>                  |
| Enter          | <Enter>                    |
| Erase Input    | <Ctrl><1>                  |
| Field Mark     | <Ctrl>*<F>                 |
| Home           | <Ctrl><8>                  |
| Insert         | <Ctrl><9>                  |
| New Line       | <Ctrl>*<N>                 |
| Reset          | <Ctrl><, >                 |
| System Request | <Ctrl><5>                  |
| Tab            | <Func><Right Arrow>        |
| Left Arrow     | <Left Arrow>               |
| Right Arrow    | <Right Arrow>              |
| Up Arrow       | <Up Arrow>                 |
| Down Arrow     | <Down Arrow>               |
| PA1            | <Ctrl><F5>                 |
| PA2            | <Ctrl><F6>                 |
| PA3            | <Ctrl><F7>                 |
|                |                            |

\*Alpha Mode

| 3270 Key | Key Sequence |
|----------|--------------|
| F1       | <F1>         |
| F2       | <F2>         |
| F3       | <F3>         |
| F4       | <F4>         |
| F5       | <F5>         |
| F6       | <F6>         |
| F7       | <F7>         |
| F8       | <F8>         |
| F9       | <F9>         |
| F10      | <F10>        |
| F11      | <Shift><F1>  |
| F12      | <Shift><F2>  |
| F13      | <Shift><F3>  |
| F14      | <Shift><F4>  |
| F15      | <Shift><F5>  |
| F16      | <Shift><F6>  |
| F17      | <Shift><F7>  |
| F18      | <Shift><F8>  |
| F19      | <Shift><F9>  |
| F20      | <Shift><F10> |
| F21      | <Ctrl><F1>   |
| F22      | <Ctrl><F2>   |
| F23      | <Ctrl><F3>   |
| F24      | <Ctrl><F4>   |

# 5250/3270 Keyboard Map

## for 38-Key MC3000

### 5250/3270 Character Map

| Char  | Key Sequence     |
|-------|------------------|
| Space | *<Space>         |
| !     | <Shift><1>       |
| “     | <Shift><Func><1> |
| #     | <Shift><3>       |
| \$    | <Shift><4>       |
| %     | <Shift><5>       |
| &     | <Shift><7>       |
| '     | <Func><1>        |
| (     | <Shift><9>       |
| )     | <Shift><0>       |
| *     | <Shift><8>       |
| +     | <Shift><Func><8> |
| ,     | <,>              |
| -     | <Func><7>        |
| .     | <.>              |
| /     | <Func><9>        |
| 0     | <0>              |
| 1     | <1>              |
| 2     | <2>              |
| 3     | <3>              |
| 4     | <4>              |
| 5     | <5>              |
| 6     | <6>              |
| 7     | <7>              |
| 8     | <8>              |
| 9     | <9>              |
| :     | <Shift><Func><6> |
| ;     | <Func><6>        |
| <     | <Shift><,>       |
| =     | <Func><8>        |
| >     | <Shift><.>       |
| ?     | <Shift><Func><9> |
| @     | <Shift><2>       |

\*Alpha Mode

| Char | Key Sequence     |
|------|------------------|
| A    | *<A>             |
| B    | *<B>             |
| C    | *<C>             |
| D    | *<D>             |
| E    | *<E>             |
| F    | *<F>             |
| G    | *<G>             |
| H    | *<H>             |
| I    | *<I>             |
| J    | *<J>             |
| K    | *<K>             |
| L    | *<L>             |
| M    | *<M>             |
| N    | *<N>             |
| O    | *<O>             |
| P    | *<P>             |
| Q    | *<Q>             |
| R    | *<R>             |
| S    | *<S>             |
| T    | *<T>             |
| U    | *<U>             |
| V    | *<V>             |
| W    | *<W>             |
| X    | *<X>             |
| Y    | *<Y>             |
| Z    | *<Z>             |
| [    | <Func><4>        |
| \    | <Func><3>        |
| ]    | <Func><5>        |
| ^    | <Shift><6>       |
| ~    | <Shift><Func><7> |
| `    | <Func><2>        |
|      |                  |

| Char           | Key Sequence     |
|----------------|------------------|
| a              | <Shift>*<A>      |
| b              | <Shift>*<B>      |
| c              | <Shift>*<C>      |
| d              | <Shift>*<D>      |
| e              | <Shift>*<E>      |
| f              | <Shift>*<F>      |
| g              | <Shift>*<G>      |
| h              | <Shift>*<H>      |
| i              | <Shift>*<I>      |
| j              | <Shift>*<J>      |
| k              | <Shift>*<K>      |
| l              | <Shift>*<L>      |
| m              | <Shift>*<M>      |
| n              | <Shift>*<N>      |
| o              | <Shift>*<O>      |
| p              | <Shift>*<P>      |
| q              | <Shift>*<Q>      |
| r              | <Shift>*<R>      |
| s              | <Shift>*<S>      |
| t              | <Shift>*<T>      |
| u              | <Shift>*<U>      |
| v              | <Shift>*<V>      |
| w              | <Shift>*<W>      |
| x              | <Shift>*<X>      |
| y              | <Shift>*<Y>      |
| z              | <Shift>*<Z>      |
| {              | <Shift><Func><4> |
|                | <Shift><Func><3> |
| }              | <Shift><Func><5> |
| ~              | <Shift><Func><2> |
| ¢ <sup>1</sup> | N/A              |
| ¬ <sup>1</sup> | N/A              |
| ¡ <sup>1</sup> | N/A              |

<sup>1</sup> Only in 5250 mode.