

5250/3270 Keyboard Map

for 35-Key LRT 3800

Booting Procedures

Boot Type	Procedure
Warm Boot	Power off the terminal. Hold down the </> and <+> keys. Power on the terminal. Release keys.
Cold Boot	Power off the terminal. Hold down the <SPACE> <FUNC> and <UP-ARROW> keys. Power on the terminal. Release keys.
Command Mode Boot	Power off the terminal. Hold down the <BKSP> and <SHIFT> keys. Power on the terminal. Release keys.

Local Terminal Functions

Local Function	Key Sequence
Keyboard State	<ALPHA>
Lamp On/Off	<CTRL><L>
Darker Display	<CTRL><SPACE>
Lighter Display	<CTRL><BKSP>
Program Information	<FUNC><CTRL><P>
Keyclicks On/Off	<FUNC><CTRL><K>
Quiet Mode On/Off	<FUNC><CTRL><Q>
Terminal Configuration	<FUNC><CTRL><C>
Radio Configuration	<CTRL><R>
Message Recall	<CTRL><Q>
Display NC TN Information	<FUNC><CTRL><X>
RF Hot-key	<FUNC><CTRL><H>
Free Cursor Mode	<CTRL><9>
Close Session on NC	<FUNC><CTRL><W>
View Mode On/Off ¹	<CTRL><6>
Scroll Left	<LEFT-ARROW>
Scroll Right	<RIGHT-ARROW>
Scroll Up	<UP-ARROW>
Scroll Down	<DOWN-ARROW>

¹ The <CTRL> and one of the scroll keys will also enable View Mode.

5250/3270 Keyboard Map

for 35-Key LRT 3800

5250 Emulation Keys

5250 Key	Key Sequence
Attention	<CTRL><A>
Backspace	<BKSP>
Back Tab	<CTRL><CLEAR>
Clear	<CTRL><C>
Delete	<CTRL><J>
Dup	<CTRL><K>
Enter	<CTRL><ENTER>
Erase Input	<CTRL><E>
Field Exit	<ENTER>
Field Minus	<SHIFT><ENTER>
Help	<CTRL><G>
Home	<CTRL><H>
Insert	<CTRL><I>
Print	<CTRL>
Reset	<CTRL><D>
Roll Up	<FUNC><SPACE>
Roll Down	<FUNC><BKSP>
System Request	<FUNC><CTRL><R>
Tab	<CLEAR>
Left Arrow	<LEFT-ARROW>
Right Arrow	<RIGHT-ARROW>
Up Arrow	<UP-ARROW>
Down Arrow	<DOWN-ARROW>

5250 Key	Key Sequence
F1	<FUNC><1>
F2	<FUNC><2>
F3	<FUNC><3>
F4	<FUNC><4>
F5	<FUNC><5>
F6	<FUNC><6>
F7	<FUNC><7>
F8	<FUNC><8>
F9	<FUNC><9>
F10	<FUNC><0>
F11	<FUNC><M>
F12	<FUNC><N>
F13	<FUNC><O>
F14	<FUNC><P>
F15	<FUNC><I>
F16	<FUNC><J>
F17	<FUNC><K>
F18	<FUNC><L>
F19	<FUNC><E>
F20	<FUNC><F>
F21	<FUNC><G>
F22	<FUNC><H>
F23	<FUNC><A>
F24	<FUNC>

5250/3270 Keyboard Map

for 35-Key LRT 3800

3270 Emulation Keys

3270 Key	Key Sequence
Attention	<CTRL><A>
Backspace	<BKSP>
Back Tab	<CTRL><CLEAR>
Clear	<CLEAR>
Clear EOF	<CTRL><F>
Delete	<CTRL><J>
Dup	<CTRL><K>
Enter	<ENTER>
Erase Input	<CTRL><E>
Field Mark	N/A
Home	<CTRL><H>
Insert	<CTRL><I>
New Line	<CTRL><ENTER>
Reset	<CTRL><D>
System Request	<FUNC><CTRL><R>
Tab	<DOWN-ARROW>
Left Arrow	<LEFT-ARROW>
Right Arrow	<RIGHT-ARROW>
Up Arrow	<UP-ARROW>
Down Arrow	<DOWN-ARROW>
PA1	<FUNC><SPACE>
PA2	<FUNC><BKSP>
PA3	<CTRL>

3270 Key	Key Sequence
F1	<FUNC><1>
F2	<FUNC><2>
F3	<FUNC><3>
F4	<FUNC><4>
F5	<FUNC><5>
F6	<FUNC><6>
F7	<FUNC><7>
F8	<FUNC><8>
F9	<FUNC><9>
F10	<FUNC><0>
F11	<FUNC><N>
F12	<FUNC><M>
F13	<FUNC><O>
F14	<FUNC><P>
F15	<FUNC><I>
F16	<FUNC><J>
F17	<FUNC><K>
F18	<FUNC><L>
F19	<FUNC><E>
F20	<FUNC><F>
F21	<FUNC><G>
F22	<FUNC><H>
F23	<FUNC><A>
F24	<FUNC>

5250/3270 Keyboard Map

for 35-Key LRT 3800

5250/3270 Character Map²

Char	Key Sequence	Char	Key Sequence	Char	Key Sequence
SPACE	<SPACE>	A	<A>	a	
!	<SHIFT><W>	B		b	
“	<SHIFT><C>	C	<C>	c	
#	<SHIFT><Y>	D	<D>	d	
\$	<SHIFT><T>	E	<E>	e	
%	<SHIFT><U>	F	<F>	f	
&	<SHIFT><Q>	G	<G>	g	
‘	<C> ³	H	<H>	h	
(	<SHIFT><S>	I	<I>	I	
)	<SHIFT><Z>	J	<J>	j	
*	<E> ³	K	<K>	k	
+	<H> ³	L	<L>	l	
,	<J> ³	M	<M>	m	
-	<G> ³	N	<N>	n	
.	<I> ³	O	<O>	o	
/	<F> ³	P	<P>	p	
0	<Z> ³	Q	<Q>	q	
1	<W> ³	R	<R>	r	
2	<X> ³	S	<S>	s	
3	<Y> ³	T	<T>	t	
4	<T> ³	U	<U>	u	
5	<U> ³	V	<V>	v	
6	<V> ³	W	<W>	w	
7	<Q> ³	X	<X>	x	
8	<R> ³	Y	<Y>	y	
9	<S> ³	Z	<Z>	z	
:	<SHIFT><L>	[	<A> ³	{	<SHIFT><A>
;	<L> ³	\	<K> ³		<SHIFT><K>
<	<SHIFT><J>	]	 ³	}	<SHIFT>
=	<D> ³	^	<SHIFT><V>	~	<SHIFT><FUNC><C>
>	<SHIFT><I>	_	<SHIFT><G>		
?	<SHIFT><F>	`	<FUNC><C>		
@	<SHIFT><X>				

² Lowercase letters are not supported.

³ ALPHA off.