

Psion Teklogix 7527 Workaboutpro 2 52- Key Keyboard Map

Booting Procedures

Boot Type	Procedure
Reset	Press and hold down the [BLUE] key and the [ENTER/ON] key simultaneously for a minimum of six seconds. When the splash screen appears, release the keys.

Local Terminal Functions

Local Function	Key Sequence
Program Information	<Alt><P>
Diagnostics	<Alt><D>
Keyclicks On/Off	<Alt><K>
Quiet Mode On/Off	<Alt><Q>
Terminal Configuration	<Alt><C>
Host Profiles	<Alt><R>
Message Recall	<Alt><M>
Free Cursor Mode	<Alt><F>
Close Session	<Alt><T>
Previous Session	N/A
Next Session	N/A
Caps Lock	<Shift><Shift>
View Mode On/Off	<Alt><Z>
Display Backlight On/Off	<Backlight>
Volume Up	<Blue><A>
Volume Down	<Blue>

Psion Teklogix 7527 Workaboutpro 2 52- Key Keyboard Map

5250 Emulation Keys

5250 Key	Key Sequence
Attention	<Ctrl><A>
Backspace	<BKSP>
Back Tab	<Shift><Tab>
Clear	<Ctrl><Blue><BKSP>
Delete	<Blue><BKSP>
Dup	<Ctrl><4>
Enter	<Ctrl><Enter>
Erase Input	<Ctrl><E>
Field Exit	<Enter>
Field Minus	<Ctrl><Orange><C>
Help	<Blue><G>
Home	<Orange><D>
Insert	<Orange><C>
Print	<Ctrl><P>
Reset	<ESC>
Roll Up	<Orange><E>
Roll Down	<Orange><K>
System Request	<Ctrl><S>
Tab	<Tab>
Left Arrow	<Left><Arrow>
Right Arrow	<Right><Arrow>
Up Arrow	<Up><Arrow>
Down Arrow	<Down><Arrow>

5250 Key	Key Sequence
F1	<Blue><1>
F2	<Blue><2>
F3	<Blue><3>
F4	<Blue><4>
F5	<Blue><5>
F6	<Blue><6>
F7	<Blue><7>
F8	<Blue><8>
F9	<Blue><9>
F10	<Blue><0>
F11	<Shift><Blue><1>
F12	<Shift><Blue><2>
F13	<Shift><Blue><3>
F14	<Shift><Blue><4>
F15	<Shift><Blue><5>
F16	<Shift><Blue><6>
F17	<Shift><Blue><7>
F18	<Shift><Blue><8>
F19	<Shift><Blue><9>
F20	<Shift><Blue><0>
F21	<Ctrl><Blue><1>
F22	<Ctrl><Blue><2>
F23	<Ctrl><Blue><3>
F24	<Ctrl><Blue><4>

Psion Teklogix 7527 Workaboutpro 2 52- Key Keyboard Map

3270 Emulation Keys

3270 Key	Key Sequence
Attention	<Ctrl><A>
Backspace	<BKSP>
Back Tab	<Shift><Tab>
Clear	<ESC>
Clear EOF	<Ctrl><O>
Delete	<Blue><BKSP>
Dup	<Ctrl><4>
Enter	<Enter>
Erase Input	<Ctrl><E>
Field Mark	<Ctrl><F>
Home	<Orange><D>
Insert	<Orange><C>
New Line	<Ctrl><N>
Reset	<Ctrl><R>
System Request	<Ctrl><S>
Tab	<Tab>
Left Arrow	<Left><Arrow>
Right Arrow	<Right><Arrow>
Up Arrow	<Up><Arrow>
Down Arrow	<Down><Arrow>
PA1	<Ctrl><1>
PA2	<Ctrl><2>
PA3	<Ctrl><3>

3270 Key	Key Sequence
F1	<Blue><1>
F2	<Blue><2>
F3	<Blue><3>
F4	<Blue><4>
F5	<Blue><5>
F6	<Blue><6>
F7	<Blue><7>
F8	<Blue><8>
F9	<Blue><9>
F10	<Blue><0>
F11	<Shift><Blue><1>
F12	<Shift><Blue><2>
F13	<Shift><Blue><3>
F14	<Shift><Blue><4>
F15	<Shift><Blue><5>
F16	<Shift><Blue><6>
F17	<Shift><Blue><7>
F18	<Shift><Blue><8>
F19	<Shift><Blue><9>
F20	<Shift><Blue><0>
F21	<Ctrl><Blue><1>
F22	<Ctrl><Blue><2>
F23	<Ctrl><Blue><3>
F24	<Ctrl><Blue><4>

Psion Teklogix 7527 Workaboutpro 2 52- Key Keyboard Map

VT-100 Emulation Keys

VT-100 Key	Key Sequence
Return	<Enter>
Backspace	<BKSP>
Tab	<Tab>
Up Arrow	<Up><Arrow>
Left Arrow	<Left><Arrow>
ESC	<ESC>
BS	<BKSP>
LF	<Ctrl><Enter>
Hard Terminal Reset	<Ctrl><Blue><H>

VT-100 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	<Ctrl><BKSP>
Backtab	<Ctrl><Tab>
Down Arrow	<Down><Arrow>
Right Arrow	<Right><Arrow>
PF1	<Blue><1>
PF2	<Blue><2>
PF3	<Blue><3>
PF4	<Blue><4>

VT-220 Emulation Keys

VT-220 Key	Key Sequence
Return	<Enter>
Backspace	<BKSP>
Tab	<Tab>
Up Arrow	<Up><Arrow>
Left Arrow	<Left><Arrow>
Hard Terminal Reset	<Ctrl><Blue><H>
Find	<Orange><D>
Insert Here	<Orange><C>
Prev Screen	<Orange><E>
PF1	<Blue><1>
PF2	<Blue><2>
PF3	<Blue><3>
PF4	<Blue><4>
BREAK ¹	<Blue><5>
F6	<Blue><6>
F7	<Blue><7>
F8	<Blue><8>
F9	<Blue><9>
F10	<Blue><0>

VT-220 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	<Ctrl><BKSP>
Backtab	<Ctrl><Tab>
Down Arrow	<Down><Arrow>
Right Arrow	<Right><Arrow>
Soft Terminal Reset	<Ctrl><Blue><S>
Select	<Ctrl><4>
Remove	<Blue><BKSP>
Next Screen	<Orange><K>
F11	<Shift><Blue><1>
F12	<Shift><Blue><2>
F13	<Shift><Blue><3>
F14	<Shift><Blue><4>
F15/Help	<Shift><Blue><5>
F16/Do	<Shift><Blue><6>
F17	<Shift><Blue><7>
F18	<Shift><Blue><8>
F19	<Shift><Blue><9>
F20	<Shift><Blue><0>

¹ The BREAK key is currently not available.

Psion Teklogix 7527 Workaboutpro 2 52- Key Keyboard Map

5250/3270/VT Character Map

Char	Key Sequence
Space	<Space>
!	<Shift><1>
“	<Orange><T>
#	<Shift><3>
\$	<Shift><4>
%	<Shift><5>
&	<Shift><7>
'	<Orange><M>
(	<Shift><9>
)	<Shift><0>
*	<Shift><8>
+	<Orange><U>
,	<Shift><,>
-	<Orange><V>
.	<.>
/	<Orange><9>
0	<0>
1	<1>
2	<2>
3	<3>
4	<4>
5	<5>
6	<6>
7	<7>
8	<8>
9	<9>
:	<Orange><S>
;	<Orange><R>
<	<Orange><1>
=	<Orange><Y>
>	<Orange><2>
?	<Orange><Z>
@	<Shift><2>

Char	Key Sequence
A	<A>
B	
C	<C>
D	<D>
E	<E>
F	<F>
G	<G>
H	<H>
I	<I>
J	<J>
K	<K>
L	<L>
M	<M>
N	<N>
O	<O>
P	<P>
Q	<Q>
R	<R>
S	<S>
T	<T>
U	<U>
V	<V>
W	<W>
X	<X>
Y	<Y>
Z	<Z>
[	<Orange><4>
\	<Orange><6>
]	<Orange><5>
^	<Shift><6>
_	<Orange><G>
`	<Orange><N>

Char	Key Sequence
a	<Shift><A>
b	<Shift>
c	<Shift><C>
d	<Shift><D>
e	<Shift><E>
f	<Shift><F>
g	<Shift><G>
h	<Shift><H>
i	<Shift><I>
j	<Shift><J>
k	<Shift><K>
l	<Shift><L>
m	<Shift><M>
n	<Shift><N>
o	<Shift><O>
p	<Shift><P>
q	<Shift><Q>
r	<Shift><R>
s	<Shift><S>
t	<Shift><T>
u	<Shift><U>
v	<Shift><V>
w	<Shift><W>
x	<Shift><X>
y	<Shift><Y>
z	<Shift><Z>
{	<Orange><7>
	<Orange><9>
}	<Orange><8>
~	<Orange><H>
€	<Orange><F>
£	<Orange><L>

Psion Teklogix 7527 Workaboutpro 2 52- Key Keyboard Map

Char	Key Sequence
^@	N/A
^A	<Ctrl><A>
^B	<Ctrl>
^C	<Ctrl><C>
^D	<Ctrl><D>
^E	<Ctrl><E>
^F	<Ctrl><F>
^G	<Ctrl><G>
^H	<Ctrl><H>
^I	<Ctrl><I>
^J	<Ctrl><J>
^K	<Ctrl><K>
^L	<Ctrl><L>
^M	<Ctrl><M>
^N	<Ctrl><N>
^O	<Ctrl><O>
^P	<Ctrl><P>
^Q	<Ctrl><Q>
^R	<Ctrl><R>
^S	<Ctrl><S>
^T	<Ctrl><T>
^U	<Ctrl><U>
^V	<Ctrl><V>
^W	<Ctrl><W>
^X	<Ctrl><X>
^Y	<Ctrl><Y>
^Z	<Ctrl><Z>
ESC	<ESC>
^\	N/A
^]	N/A
^^	N/A
^_	N/A