

VT/HP Keyboard Map

for SPT 1740

Booting Procedures

Boot Type	Procedure
Soft Reset	With the terminal face down, open the right battery lock. Press the reset button under the battery lock using paper clip or similar object without a sharp tip.
Hard Reset <i>WARNING: This will delete all applications and records from memory.</i>	Hold down the Power button. With the terminal face down, open the right battery lock. Press the reset button under the battery lock using paper clip or similar object without a sharp tip. Release the Power button. Confirm the action by pressing the up scroll button.

Local Terminal Functions

Local Function	Key Sequence
Backlight	Press and hold the power button until backlight comes on.
Contrast	Press the contrast button.
Program Information	[Cfg]<Prog Info>
Keyclicks On/Off	[Cfg]<KeyClks>
Warning Bells On/Off	[Cfg]<Quiet>
Terminal Configuration	[Cfg]<TermConfig>
Host Profiles	Press the Menu key. Select Host Profiles.
VT/HP Terminal Setup	[Cfg]<VT/HP Cfg>
Close Session	[Cfg]<Close>
Previous Session	[Cfg]<Prev Sess>
Next Session	[Cfg]<Next Sess>
Caps Lock	[Alpha]<Caps>

VT/HP Keyboard Map

for SPT 1740

VT-100 Emulation Keys

VT-100 Key	Key Sequence
Return	[Alpha]<Enter>
Backspace	[Alpha]<←>
Tab	[Alpha]<Tab>
Up Arrow	[Alpha]<?>
Left Arrow	[Alpha]<? >
ESC	[Func]<Shft><F11>
BS	[Func]<Shft><F12>
LF	[Func]<Shft><F13>
Hard Terminal Reset	[Alpha]<Alt><H>

VT-100 Key	Key Sequence
Enter	[Alpha]<Alt><E>
Delete	[Alpha]<Ctrl><←>
Backtab	[Alpha]<Shft><Tab>
Down Arrow	[Alpha]<?>
Right Arrow	[Alpha]<? >
PF1	[Func]<F1>
PF2	[Func]<F2>
PF3	[Func]<F3>
PF4	[Func]<F4>

VT-220 Emulation Keys

VT-220 Key	Key Sequence
Return	[Alpha]<Enter>
Backspace (Delete)	[Alpha]<←>
Tab	[Alpha]<Tab>
Up Arrow	[Alpha]<?>
Left Arrow	[Alpha]<? >
Hard Terminal Reset	[Alpha]<Alt><H>
Find	[Func]<Find>
Insert Here	[Num]<Ins>
Prev Screen	[Func]<Prev>
PF1	[Func]<F1>
PF2	[Func]<F2>
PF3	[Func]<F3>
PF4	[Func]<F4>
BREAK ¹	[Func]<F5>
F6	[Func]<F6>
F7	[Func]<F7>
F8	[Func]<F8>
F9	[Func]<F9>
F10	[Func]<F10>

VT-220 Key	Key Sequence
Enter	[Alpha]<Alt><E>
Delete	[Alpha]<Ctrl><←>
Backtab	[Alpha]<Shft><Tab>
Down Arrow	[Alpha]<?>
Right Arrow	[Alpha]<? >
Soft Terminal Reset	[Alpha]<Alt><S>
Select	[Func]<Sel>
Remove	[Num]<Rem>
Next Screen	[Func]<Next>
F11	[Func]<Shft><F11>
F12	[Func]<Shft><F12>
F13	[Func]<Shft><F13>
F14	[Func]<Shft><F14>
F15/Help	[Func]<Shft><F15>
F16/Do	[Func]<Shft><F16>
F17	[Func]<Shft><F17>
F18	[Func]<Shft><F18>
F19	[Func]<Shft><F19>
F20	[Func]<Shft><F20>

¹ The BREAK key is currently not available.

VT/HP Keyboard Map

for SPT 1740

HP Emulation Keys²

HP Key	Key Sequence
Return	[Alpha]<Enter>
Backspace	[Alpha]<←>
Tab	[Alpha]<Tab>
Up Arrow	[Alpha]<?>
Left Arrow	[Alpha]<? >
Insert Line	[Func][Shft]<Ins Ln>
Insert Char	[Func][Shft]<Ins Chr>
Hard Terminal Reset	[Alpha]<Alt><H>
Prev	[Func][Shft]<Prev>
Clear Line	[Func][Shft]<Clr Ln>
Insert Char w/ wrap	[Func][Shft]<Ins Wrap>
Scroll Down	[Func][Shft]<Scroll Dn>
F1	[Func]<F1>
F2	[Func]<F2>
F3	[Func]<F3>
F4	[Func]<F4>
User Key Menu	[Func]<F10>

HP Key	Key Sequence
Enter	[Alpha]<Alt><E>
Delete	[Alpha]<Ctrl><←>
Backtab	[Alpha]<Shft><Tab>
Down Arrow	[Alpha]<?>
Right Arrow	[Alpha]<? >
Delete Line	[Func][Shft]<Del Ln>
Delete Char	[Func][Shft]<Del Chr>
Soft Terminal Reset	[Alpha]<Alt><S>
Next	[Func][Shft]<Next>
Clear Display	[Func][Shft]<Clr Dsp>
Delete Char w/ wrap	[Func][Shft]<Del Chr>
Scroll Up	[Func][Shft]<Scroll Up>
F5	[Func]<F5>
F6	[Func]<F6>
F7	[Func]<F7>
F8	[Func]<F8>
System Modes Menu	[Func]<Shft><F20>

² The BREAK and STOP keys are currently not available.

VT/HP Keyboard Map

for SPT 1740

VT/HP Character Map

Char	Key Sequence
^@	[Alpha]<Ctrl><^@>
^A	[Alpha]<Ctrl><A>
^B	[Alpha]<Ctrl>
^C	[Alpha]<Ctrl><C>
^D	[Alpha]<Ctrl><D>
^E	[Alpha]<Ctrl><E>
^F	[Alpha]<Ctrl><F>
^G	[Alpha]<Ctrl><G>
^H	[Alpha]<Ctrl><H>
^I	[Alpha]<Ctrl><I>
^J	[Alpha]<Ctrl><J>
^K	[Alpha]<Ctrl><K>
^L	[Alpha]<Ctrl><L>
^M	[Alpha]<Ctrl><M>
^N	[Alpha]<Ctrl><N>
^O	[Alpha]<Ctrl><O>
^P	[Alpha]<Ctrl><P>
^Q	[Alpha]<Ctrl><Q>
^R	[Alpha]<Ctrl><R>
^S	[Alpha]<Ctrl><S>
^T	[Alpha]<Ctrl><T>
^U	[Alpha]<Ctrl><U>
^V	[Alpha]<Ctrl><V>
^W	[Alpha]<Ctrl><W>
^X	[Alpha]<Ctrl><X>
^Y	[Alpha]<Ctrl><Y>
^Z	[Alpha]<Ctrl><Z>
ESC	[Alpha]<Esc>
^\ ^]	[Alpha]<Ctrl><[> [Alpha]<Ctrl><]>
^^	[Alpha]<Ctrl><^>
^_	[Alpha]<Ctrl><_>
SPACE	[Alpha]<SPACE>
!	[Punc]<!>
"	[Punc]<">
#	[Punc]<#>
\$	[Punc]<\$>
%	[Punc]<%>
&	[Punc]<&>
'	[Punc]<'>
(	[Punc]<(>
)	[Punc]<)>
*	[Punc]<*>

Char	Key Sequence
+	[Punc]<+>
,	[Punc]<,>
-	[Punc]<->
.	[Punc]<.>
/	[Punc]</>
0	[Num]<0>
1	[Num]<1>
2	[Num]<2>
3	[Num]<3>
4	[Num]<4>
5	[Num]<5>
6	[Num]<6>
7	[Num]<7>
8	[Num]<8>
9	[Num]<9>
:	[Punc]<:>
;	[Punc]<:>
<	[Punc]<<>
=	[Punc]<=>
>	[Punc]<>>
?	[Punc]<?>
@	[Punc]<@>
A	[Alpha]<Shft><A>
B	[Alpha]<Shft>
C	[Alpha]<Shft><C>
D	[Alpha]<Shft><D>
E	[Alpha]<Shft><E>
F	[Alpha]<Shft><F>
G	[Alpha]<Shft><G>
H	[Alpha]<Shft><H>
I	[Alpha]<Shft><I>
J	[Alpha]<Shft><J>
K	[Alpha]<Shft><K>
L	[Alpha]<Shft><L>
M	[Alpha]<Shft><M>
N	[Alpha]<Shft><N>
O	[Alpha]<Shft><O>
P	[Alpha]<Shft><P>
Q	[Alpha]<Shft><Q>
R	[Alpha]<Shft><R>
S	[Alpha]<Shft><S>
T	[Alpha]<Shft><T>
U	[Alpha]<Shft><U>

Char	Key Sequence
V	[Alpha]<Shft><V>
W	[Alpha]<Shft><W>
X	[Alpha]<Shft><X>
Y	[Alpha]<Shft><Y>
Z	[Alpha]<Shft><Z>
[	[Punc]<[>
\	[Punc]<[>
]	[Punc]<]>
^	[Punc]<^>
_	[Punc]<_>
`	[Punc]<'>
a	[Alpha]<a>
b	[Alpha]
c	[Alpha]<c>
d	[Alpha]<d>
e	[Alpha]<e>
f	[Alpha]<f>
g	[Alpha]<g>
h	[Alpha]<h>
i	[Alpha]<i>
j	[Alpha]<j>
k	[Alpha]<k>
l	[Alpha]<l>
m	[Alpha]<m>
n	[Alpha]<n>
o	[Alpha]<o>
p	[Alpha]<p>
q	[Alpha]<q>
r	[Alpha]<r>
s	[Alpha]<s>
t	[Alpha]<t>
u	[Alpha]<u>
v	[Alpha]<v>
w	[Alpha]<w>
x	[Alpha]<x>
y	[Alpha]<y>
z	[Alpha]<z>
{	[Punc]<{>
	[Punc]< >
}	[Punc]<}>
~	[Punc]<~>
DEL	<Ctrl><←>