

5250/3270 Keyboard Map

for 23-Key PDT 8000

Booting Procedures

Boot Type	Procedure
Soft Reset	Press and hold power for about 10 seconds
Hard Reset	Open Battery Door, press and release Power Key + Scan button, close Battery Door

Local Terminal Functions

Local Function	Key Sequence
Program Information	N/A
Diagnostics	N/A
Keyclicks On/Off	N/A
Quiet Mode On/Off	N/A
Terminal Configuration	N/A
Host Profiles	N/A
Message Recall	N/A
Free Cursor Mode	N/A
Close Session	N/A
Previous Session	N/A
Next Session	N/A
Caps Lock	<A>
Increase Contrast	<Shift><Right Arrow>
Decrease Contrast	<Shift><Left Arrow>
Calibrate screen	<Shift><2>

<F> = Envelope key = Func state - cursor displays "F"

<a> = Open Book key = Lower case Alpha state - cursor displays "a"

<A> = Open Book key = Upper case Alpha state - cursor displays "A"

5250/3270 Keyboard Map

for 23-Key PDT 8000

5250 Emulation Keys

5250 Key	Key Sequence
Attention	N/A
Backspace	<Shift><7>
Back Tab	<a><Tab><Tab>
Clear	N/A
Delete	<Shift><1>
Dup	<Shift><9>
Enter	<A><Ent><Ent>
Erase Input	N/A
Field Exit	<Ent>
Field Minus	N/A
Help	N/A
Home	<Shift><3>
Insert	N/A
Print	N/A
Reset	<Shift><0>
Roll Up	<Shift><Up>
Roll Down	<Shift><Down>
System Request	N/A
Tab	<Tab>
Left Arrow	<Left><Arrow>
Right Arrow	<Right><Arrow>
Up Arrow	<Up><Arrow>
Down Arrow	<Down><Arrow>

5250 Key	Key Sequence
F1	<F><1>
F2	<F><2>
F3	<F><3>
F4	<F><4>
F5	<F><5>
F6	<F><6>
F7	<F><7>
F8	<F><8>
F9	<F><9>
F10	<F><0>
F11	<F><1><1>
F12	<F><2><2>
F13	<F><3><3>
F14	<F><4><4>
F15	<F><5><5>
F16	<F><6><6>
F17	<F><7><7>
F18	<F><8><8>
F19	<F><9><9>
F20	<F><0><0>
F21	<F><1><1><1>
F22	<F><2><2><2>
F23	<F><3><3><3>
F24	<F><4><4><4>

<F> = Envelope key = Func state - cursor displays "F"

<a> = Open Book key = Lower case Alpha state - cursor displays "a"

<A> = Open Book key = Upper case Alpha state - cursor displays "A"

5250/3270 Keyboard Map

for 23-Key PDT 8000

3270 Emulation Keys

3270 Key	Key Sequence
Attention	N/A
Backspace	<Shift><7>
Back Tab	<a><Tab><Tab>
Clear	<Shift><0>
Clear EOF	N/A
Delete	<Shift><1>
Dup	<Shift><9>
Enter	<Ent>
Erase Input	N/A
Field Mark	N/A
Home	<Shift><3>
Insert	N/A
New Line	N/A
Reset	N/A
System Request	N/A
Tab	<Tab>
Left Arrow	<Left><Arrow>
Right Arrow	<Right><Arrow>
Up Arrow	<Up><Arrow>
Down Arrow	<Down><Arrow>
PA1	<a><1>
PA2	<a><1><1>
PA3	<a><1><1><1>

3270 Key	Key Sequence
F1	<F><1>
F2	<F><2>
F3	<F><3>
F4	<F><4>
F5	<F><5>
F6	<F><6>
F7	<F><7>
F8	<F><8>
F9	<F><9>
F10	<F><0>
F11	<F><1><1>
F12	<F><2><2>
F13	<F><3><3>
F14	<F><4><4>
F15	<F><5><5>
F16	<F><6><6>
F17	<F><7><7>
F18	<F><8><8>
F19	<F><9><9>
F20	<F><0><0>
F21	<F><1><1><1>
F22	<F><2><2><2>
F23	<F><3><3><3>
F24	<F><4><4><4>

<F> = Envelope key = Func state - cursor displays "F"

<a> = Open Book key = Lower case Alpha state - cursor displays "a"

<A> = Open Book key = Upper case Alpha state - cursor displays "A"

5250/3270 Keyboard Map

for 23-Key PDT 8000

5250/3270 Character Map

Char	Key Sequence
Space	<a><Next>
!	N/A
"	N/A
#	N/A
\$	N/A
%	N/A
&	N/A
'	N/A
(	N/A
)	N/A
*	N/A
+	N/A
,	N/A
-	N/A
.	N/A
/	N/A
0	<0>
1	<1>
2	<2>
3	<3>
4	<4>
5	<5>
6	<6>
7	<7>
8	<8>
9	<9>
:	N/A
;	N/A
<	N/A
=	N/A
>	N/A
?	N/A
@	N/A

Char	Key Sequence
A	<A><2>
B	<A><2><2>
C	<A><2><2><2>
D	<A><3>
E	<A><3><3>
F	<A><3><3><3>
G	<A><4>
H	<A><4><4>
I	<A><4><4><4>
J	<A><5>
K	<A><5><5>
L	<A><5><5><5>
M	<A><6>
N	<A><6><6>
O	<A><6><6><6>
P	<A><7>
Q	<A><7><7>
R	<A><7><7><7>
S	<A><7><7><7><7>
T	<A><8>
U	<A><8><8>
V	<A><8><8><8>
W	<A><9>
X	<A><9><9>
Y	<A><9><9><9>
Z	<A><9><9><9><9>
[	N/A
\	N/A
]	N/A
^	N/A
_	N/A
`	N/A

Char	Key Sequence
a	<a><2>
b	<a><2><2>
c	<a><2><2><2>
d	<a><3>
e	<a><3><3>
f	<a><3><3><3>
g	<a><4>
h	<a><4><4>
i	<a><4><4><4>
j	<a><5>
k	<a><5><5>
l	<a><5><5><5>
m	<a><6>
n	<a><6><6>
o	<a><6><6><6>
p	<a><7>
q	<a><7><7>
r	<a><7><7><7>
s	<a><7><7><7><7>
t	<a><8>
u	<a><8><8>
v	<a><8><8><8>
w	<a><9>
x	<a><9><9>
y	<a><9><9><9>
z	<a><9><9><9><9>
{	N/A
	N/A
}	N/A
~	N/A
¢ ¹	N/A
¬ ¹	N/A
¡ ¹	N/A

<F> = Envelope key = Func state - cursor displays "F"

<a> = Open Book key = Lower case Alpha state - cursor displays "a"

<A> = Open Book key = Upper case Alpha state - cursor displays "A"