

5250/3270 Keyboard Map

for 37-Key PDT 8100

Booting Procedures

Boot Type	Procedure
Soft Reset	Backlight + Alpha + Function
Hard Reset	Function + Reset(located in the battery compartment)

Local Terminal Functions

Local Function	Key Sequence
Program Information	<Func><O><Alpha><P>
Diagnostics	<Func><O><Alpha><D>
Keyclicks On/Off	<Func><O><Alpha><K>
Quiet Mode On/Off	<Func><O><Alpha><Q>
Terminal Configuration	<Func><O><Alpha><C>
Host Profiles	<Func><O><Alpha><R>
Message Recall	<Func><O><BkSp>
Free Cursor Mode	<Func><O><Alpha><F>
Close Session	<Func><O><Alpha><T>
Previous Session	<Func><O><X>
Next Session	<Func><O><E>
Caps Lock	<Func><Shift>
View Mode On/Off	<Func><O><Alpha><Z>
Scroll Left	N/A
Scroll Right	N/A
Scroll Up	<Func><C>
Scroll Down	<Func><H>

5250/3270 Keyboard Map

for 37-Key PDT 8100

5250 Emulation Keys

5250 Key	Key Sequence
Attention	<Func><P><Alpha><A>
Backspace	<Bk-Sp>
Back Tab	<Func><P>
Clear	<Func><P><Alpha><C>
Delete	<Func><P><E>
Dup	<Func><O><I>
Enter	<Send>
Erase Input	<Func><P><Alpha><E>
Field Exit	<Func><P><Alpha><M>
Field Minus	<Func><P><M>
Help	<Func><P><Alpha><G>
Home	<Func><O><G>
Insert	<Func><P><J>
Print	<Func><P><Alpha><P>
Reset	<Func><Enter>
Roll Up	<Func><O><C>
Roll Down	<Func><O><H>
System Request	<Func><P><Alpha><S>
Tab	<Func><K>
Left Arrow	*<G>
Right Arrow	*<I>
Up Arrow	*<C>
Down Arrow	*<H>

5250 Key	Key Sequence
F1	<Func><1>
F2	<Func><2>
F3	<Func><3>
F4	<Func><4>
F5	<Func><5>
F6	<Func><6>
F7	<Func><7>
F8	<Func><8>
F9	<Func><9>
F10	<Func><0>
F11	<Shift><Func><1>
F12	<Shift><Func><2>
F13	<Shift><Func><3>
F14	<Shift><Func><4>
F15	<Shift><Func><5>
F16	<Shift><Func><6>
F17	<Shift><Func><7>
F18	<Shift><Func><8>
F19	<Shift><Func><9>
F20	<Shift><Func><0>
F21	<Func><P><Func><1>
F22	<Func><P><Func><2>
F23	<Func><P><Func><3>
F24	<Func><P><Func><4>

*Alpha Mode

5250/3270 Keyboard Map

for 37-Key PDT 8100

3270 Emulation Keys

3270 Key	Key Sequence
Attention	<Func><P><Alpha><A>
Backspace	<Bk-Sp>
Back Tab	<Func><P>
Clear	<Func><P><Alpha><C>
Clear EOF	<Func><P><Alpha><O>
Delete	<Func><P><E>
Dup	<Func><O><I>
Enter	<Send>
Erase Input	<Func><P><Alpha><E>
Field Mark	<Func><P><Alpha><F>
Home	<Func><O><G>
Insert	<Func><P><J>
New Line	<Func><O><Y>
Reset	<Shift><BkSp>
System Request	<Func><P><Alpha><S>
Tab	<Func><K>
Left Arrow	*<G>
Right Arrow	*<I>
Up Arrow	*<C>
Down Arrow	*<H>
PA1	<Func><P><U>
PA2	<Func><P><V>
PA3	<Func><P><W>

3270 Key	Key Sequence
F1	<Func><1>
F2	<Func><2>
F3	<Func><3>
F4	<Func><4>
F5	<Func><5>
F6	<Func><6>
F7	<Func><7>
F8	<Func><8>
F9	<Func><9>
F10	<Func><P><Y>
F11	<Shift><Func><1>
F12	<Shift><Func><2>
F13	<Shift><Func><3>
F14	<Shift><Func><4>
F15	<Shift><Func><5>
F16	<Shift><Func><6>
F17	<Shift><Func><7>
F18	<Shift><Func><8>
F19	<Shift><Func><9>
F20	<Shift><Func><0>
F21	<Func><P><Func><1>
F22	<Func><P><Func><2>
F23	<Func><P><Func><3>
F24	<Func><P><Func><4>

* Alpha Mode

5250/3270 Keyboard Map

for 37-Key PDT 8100

5250/3270 Character Map

Char	Key Sequence
Space	<Func><Bk-Sp>
!	<Shift><U>
“	<Shift><K>
#	<Shift><W>
\$	<Shift><Q>
%	<Shift><R>
&	<Shift><L>
'	<K>
(<Shift><N>
)	<Shift><Y>
*	<Shift><M>
+	N/A
,	<P>
-	<X>
.	<Z>
/	<J>
0	<0>
1	<1>
2	<2>
3	<3>
4	<4>
5	<5>
6	<6>
7	<7>
8	<8>
9	<9>
:	<Shift><A>
;	<A>
<	<Shift><P>
=	<E>
>	<Shift><Z>
?	<Shift><J>
@	<Shift><V>

Char	Key Sequence
A	*<A>
B	*
C	*<C>
D	*<D>
E	*<E>
F	*<F>
G	*<G>
H	*<H>
I	*<I>
J	*<J>
K	*<K>
L	*<L>
M	*<M>
N	*<N>
O	*<O>
P	*<P>
Q	*<Q>
R	*<R>
S	*<S>
T	*<T>
U	*<U>
V	*<V>
W	*<W>
X	*<X>
Y	*<Y>
Z	*<Z>
[
\	<F>
]	<D>
^	<Shift><S>
_	<Shift><X>
`	N/A

Char	Key Sequence
a	*<Shift><A>
b	*<Shift>
c	*<Shift><C>
d	*<Shift><D>
e	*<Shift><E>
f	*<Shift><F>
g	*<Shift><G>
h	*<Shift><H>
i	*<Shift><I>
j	*<Shift><J>
k	*<Shift><K>
l	*<Shift><L>
m	*<Shift><M>
n	*<Shift><N>
o	*<Shift><O>
p	*<Shift><P>
q	*<Shift><Q>
r	*<Shift><R>
s	*<Shift><S>
t	*<Shift><T>
u	*<Shift><U>
v	*<Shift><V>
w	*<Shift><W>
x	*<Shift><X>
y	*<Shift><Y>
z	*<Shift><Z>
{	<Shift>
	<Shift><F>
}	<Shift><D>
~	N/A
¢ ¹	
¬ ¹	
¡ ¹	

*Alpha Mode

¹ Only in 5250 mode.