

5250/3270 Keyboard Map

for 47-Key PDT 8100

Booting Procedures

Boot Type	Procedure
Soft Reset	Backlight + End + Function
Hard Reset	Function + Reset(located in the battery compartment)

Local Terminal Functions

Local Function	Key Sequence
Program Information	<Func><V><P>
Diagnostics	<Func><V><D>
Keyclicks On/Off	<Func><V><K>
Quiet Mode On/Off	<Func><V><Q>
Terminal Configuration	<Func><V><C>
Host Profiles	<Func><V><R>
Message Recall	<Func><V><BkSp>
Free Cursor Mode	<Func><V><F>
Close Session	<Func><V><T>
Previous Session	<Shift><Func><M>
Next Session	<Shift><Func><N>
Caps Lock	<Func><Shift>
View Mode On/Off	<Func><V><Z>
Scroll Left	<Func><G>
Scroll Right	<Func><I>
Scroll Up	<Func><C>
Scroll Down	<Func><H>

5250/3270 Keyboard Map

for 47-Key PDT 8100

5250 Emulation Keys

5250 Key	Key Sequence
Attention	<Func><P><A>
Backspace	<Bk-Sp>
Back Tab	<Shift><Func><K>
Clear	<Func><P><C>
Delete	<Shift><BkSp>
Dup	N/A
Enter	<Send>
Erase Input	N/A
Field Exit	<Enter>
Field Minus	N/A
Help	<Func><P><G>
Home	<Func><P><.>
Insert	<Shift><Func><I>
Print	<Func><P><P>
Reset	<Func><Clear>
Roll Up	<Shift><Func><C>
Roll Down	<Shift><Func><H>
System Request	<Func><P><S>
Tab	<Func><K>
Left Arrow	<Func><G>
Right Arrow	<Func><I>
Up Arrow	<Func><C>
Down Arrow	<Func><H>

5250 Key	Key Sequence
F1	<Func><1>
F2	<Func><2>
F3	<Func><3>
F4	<Func><4>
F5	<Func><5>
F6	<Func><6>
F7	<Func><7>
F8	<Func><8>
F9	<Func><9>
F10	<Func><0>
F11	<Shift><Func><1>
F12	<Shift><Func><2>
F13	<Shift><Func><3>
F14	<Shift><Func><4>
F15	<Shift><Func><5>
F16	<Shift><Func><6>
F17	<Shift><Func><7>
F18	<Shift><Func><8>
F19	<Shift><Func><9>
F20	<Shift><Func><0>
F21	<Func><P><Func><1>
F22	<Func><P><Func><2>
F23	<Func><P><Func><3>
F24	<Func><P><Func><4>

5250/3270 Keyboard Map

for 47-Key PDT 8100

3270 Emulation Keys

3270 Key	Key Sequence
Attention	<Func><P><A>
Backspace	<Bk-Sp>
Back Tab	<Shift><Func><K>
Clear	<Func><P><C>
Clear EOF	<Shift><Clear>
Delete	<Shift><BkSp>
Dup	N/A
Enter	<Send>
Erase Input	N/A
Field Mark	<Shift><Func><G>
Home	<Func><P><. >
Insert	<Shift><Func><I>
New Line	N/A
Reset	<Clear>
System Request	<Func><P><9>
Tab	<Func><K>
Left Arrow	<Func><G>
Right Arrow	<Func><I>
Up Arrow	<Func><C>
Down Arrow	<Func><H>
PA1	<Func><P><5>
PA2	<Func><P><6>
PA3	<Func><P><7>

3270 Key	Key Sequence
F1	<Func><1>
F2	<Func><2>
F3	<Func><3>
F4	<Func><4>
F5	<Func><5>
F6	<Func><6>
F7	<Func><7>
F8	<Func><8>
F9	<Func><9>
F10	<Func><0>
F11	<Shift><Func><1>
F12	<Shift><Func><2>
F13	<Shift><Func><3>
F14	<Shift><Func><4>
F15	<Shift><Func><5>
F16	<Shift><Func><6>
F17	<Shift><Func><7>
F18	<Shift><Func><8>
F19	<Shift><Func><9>
F20	<Shift><Func><0>
F21	<Func><P><Func><1>
F22	<Func><P><Func><2>
F23	<Func><P><Func><3>
F24	<Func><P><Func><4>

5250/3270 Keyboard Map

for 47-Key PDT 8100

5250/3270 Character Map

Char	Key Sequence
Space	<Func><Bk-Sp>
!	<Shift><1>
“	<Shift><Func><. >
#	<Shift><3>
\$	<Shift><4>
%	<Shift><5>
&	<Shift><7>
'	<Func><. >
(<Shift><9>
)	<Shift><0>
*	<Shift><8>
+	N/A
,	<Func><M>
-	<Func><O>
.	<. >
/	<Func><L>
0	<0>
1	<1>
2	<2>
3	<3>
4	<4>
5	<5>
6	<6>
7	<7>
8	<8>
9	<9>
:	<Shift><Func><U>
;	<Func><U>
<	N/A
=	<Func><T>
>	<Shift><. >
?	<Shift><Func><L>
@	<Shift><2>

Char	Key Sequence
A	<Shift><A>
B	<Shift>
C	<Shift><C>
D	<Shift><D>
E	<Shift><E>
F	<Shift><F>
G	<Shift><G>
H	<Shift><H>
I	<Shift><I>
J	<Shift><J>
K	<Shift><K>
L	<Shift><L>
M	<Shift><M>
N	<Shift><N>
O	<Shift><O>
P	<Shift><P>
Q	<Shift><Q>
R	<Shift><R>
S	<Shift><S>
T	<Shift><T>
U	<Shift><U>
V	<Shift><V>
W	<Shift><W>
X	<Shift><X>
Y	<Shift><Y>
Z	<Shift><Z>
[<Func><Q>
\	<Func><S>
]	<Func><R>
^	<Shift><6>
_	<Shift><Func><O>
`	N/A

Char	Key Sequence
a	<A>
b	
c	<C>
d	<D>
e	<E>
f	<F>
g	<G>
h	<H>
i	<I>
j	<J>
k	<K>
l	<L>
m	<M>
n	<N>
o	<O>
p	<P>
q	<Q>
r	<R>
s	<S>
t	<T>
u	<U>
v	<V>
w	<W>
x	<X>
y	<Y>
z	<Z>
{	<Shift><Func><Q>
	<Shift><Func><S>
}	<Shift><Func><R>
~	N/A