

VT/HP Keyboard Map

for 37-Key PDT 8100

Booting Procedures

Boot Type	Procedure
Soft Reset	Backlight + Alpha + Function
Hard Reset	Function + Reset(located in the battery compartment)

Local Terminal Functions

Local Function	Key Sequence
Program Information	<Func><O><Alpha><P>
Diagnostics	<Func><O><Alpha><D>
Keyclicks On/Off	<Func><O><Alpha><K>
Quiet Mode	<Func><O><Alpha><Q>
Terminal Configuration	<Func><O><Alpha><C>
Host Configuration	<Func><O><Alpha><R>
VT/HP Terminal Setup	N/A
Close Session	<Func><O><Alpha><T>
Previous Session	<Func><O><X>
Next Session	<Func><O><E>
Caps Lock	<Func><Shift>
View Mode On/Off	<Func><O><Alpha><Z>
Scroll Left	<Func><G>
Scroll Right	<Func><I>
Scroll Up	<Func><C>
Scroll Down	<Func><H>

VT/HP Keyboard Map

for 37-Key PDT 8100

VT-100 Emulation Keys

VT-100 Key	Key Sequence
Return	<Send>
Backspace	<Bk-Sp>
Tab	<Func><K>
Up Arrow	<Func><C>
Left Arrow	<Func><P><L>
ESC	<Func><Enter>
BS	<Bk-Sp>
LF	<Func><P><Enter>
Hard Terminal Reset	N/A

VT-100 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	<Bk-Sp>
Backtab	<Shift><Func><K>
Down Arrow	<Func><H>
Right Arrow	<Func><P><N>
PF1	<Func><U>
PF2	<Func><V>
PF3	<Func><W>
PF4	<Func><Q>

VT-220 Emulation Keys

VT-220 Key	Key Sequence
Return	<Send>
Backspace	<BkSp>
Tab	<Func><K>
Up Arrow	<Func><C>
Left Arrow	<Func><P><L>
Hard Terminal Reset	N/A
Find	<Func><O><G>
Insert Here	<Func><P><J>
Prev Screen	<Func><O><C>
PF1	<Func><U>
PF2	<Func><V>
PF3	<Func><W>
PF4	<Func><Q>
BREAK ¹	N/A
F6	<Func><S>
F7	<Func><L>
F8	<Func><M>
F9	<Func><N>
F10	<Func><0>

VT-220 Key	Key Sequence
Enter	<Enter>
Backspace(Del)	<Func><P><Alpha><BkSp>
Backtab	<Shift><Func><K>
Down Arrow	<Func><H>
Right Arrow	<Func><P><N>
Soft Terminal Reset	N/A
Select	<Func><O><I>
Remove	<Func><P><E>
Next Screen	<Func><O><H>
F11	<Shift><Func><U>
F12	<Shift><Func><V>
F13	<Shift><Func><W>
F14	<Shift><Func><Q>
F15/Help	<Shift><Func><R>
F16/Do	<Shift><Func><S>
F17	<Shift><Func><L>
F18	<Shift><Func><M>
F19	<Shift><Func><N>
F20	<Shift><Func><Y>

¹ The BREAK key is currently not available.

VT/HP Keyboard Map

for 37-Key PDT 8100

HP Emulation Keys²

HP Key	Key Sequence
Return	<Send>
Backspace	<BkSp>
Tab	<Func><K>
Up Arrow	<Func><C>
Left Arrow	<Func><P><L>
Insert Line	<Func><P><J>
Insert Char	<Func><P><E>
Hard Terminal Reset	<Func><O><Alpha><H>
Prev	<Func><O><C>
Clear Line	<Shift><Func><W>
Insert Char with wrap	<Shift><Func><R>
Scroll Down	<Shift><Func><L>
F1	<Func><U>
F2	<Func><V>
F3	<Func><W>
F4	<Func><Q>
User Key Menu	<Func><P><Y>

HP Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	<BkSp>
Backtab	<Shift><Func><K>
Down Arrow	<Func><H>
Right Arrow	<Func><P><N>
Delete Line	<Func><O><G>
Delete Char	<Func><O><I>
Soft Terminal Reset	N/A
Next	<Func><O><H>
Clear Display	<Shift><Func><Q>
Delete Char with wrap	<Shift><Func><S>
Scroll Up	<Shift><Func><M>
F5	<Func><R>
F6	<Func><S>
F7	<Func><L>
F8	<Func><M>
System Modes Menu	<Shift><Func><Y>

² The BREAK and STOP keys are currently not available.

VT/HP Keyboard Map

for 37-Key PDT 8100

VT/HP Character Map

Char	Key Sequence
^@	<Func><P><V>
^A	<Func><P><Alpha><A>
^B	<Func><P><Alpha>
^C	<Func><P><Alpha><C>
^D	<Func><P><Alpha><D>
^E	<Func><P><Alpha><E>
^F	<Func><P><Alpha><F>
^G	<Func><P><Alpha><G>
^H	<Func><P><Alpha><H>
^I	<Func><P><Alpha><I>
^J	<Func><P><Alpha><J>
^K	<Func><P><Alpha><K>
^L	<Func><P><Alpha><L>
^M	<Func><P><Alpha><M>
^N	<Func><P><Alpha><N>
^O	<Func><P><Alpha><O>
^P	<Func><P><Alpha><P>
^Q	<Func><P><Alpha><Q>
^R	<Func><P><Alpha><R>
^S	<Func><P><Alpha><S>
^T	<Func><P><Alpha><T>
^U	<Func><P><Alpha><U>
^V	<Func><P><Alpha><V>
^W	<Func><P><Alpha><W>
^X	<Func><P><Alpha><X>
^Y	<Func><P><Alpha><Y>
^Z	<Func><P><Alpha><Z>
ESC	<Clear>
^\ ^] ^^ ^_	N/A
Space	<Func><Bk-Sp>
!	<Shift><U> *
“	<Shift><K> *
#	<Shift><W> *
\$	<Shift><Q> *
%	<Shift><R> *
&	<Shift><L> *
'	<K> *
(<Shift><N> *
)	<Shift><Y> *
*	<Shift><M> *

Char	Key Sequence
+	N/A
,	<P> *
-	<X> *
.	<Z> *
/	<J> *
0	<0> *
1	<1> *
2	<2> *
3	<3> *
4	<4> *
5	<5> *
6	<6> *
7	<7> *
8	<8> *
9	<9> *
:	<Shift><A>
;	<A> *
<	<Shift><P>
=	<E> *
>	<Shift><Z>
?	<Shift><J>
@	<Shift><V>
A	<Alpha><Shift><A>
B	<Alpha><Shift>
C	<Alpha><Shift><C>
D	<Alpha><Shift><D>
E	<Alpha><Shift><E>
F	<Alpha><Shift><F>
G	<Alpha><Shift><G>
H	<Alpha><Shift><H>
I	<Alpha><Shift><I>
J	<Alpha><Shift><J>
K	<Alpha><Shift><K>
L	<Alpha><Shift><L>
M	<Alpha><Shift><M>
N	<Alpha><Shift><N>
O	<Alpha><Shift><O>
P	<Alpha><Shift><P>
Q	<Alpha><Shift><Q>
R	<Alpha><Shift><R>
S	<Alpha><Shift><S>
T	<Alpha><Shift><T>
U	<Alpha><Shift><U>

Char	Key Sequence
V	<Alpha><Shift><V>
W	<Alpha><Shift><W>
X	<Alpha><Shift><X>
Y	<Alpha><Shift><Y>
Z	<Alpha><Shift><Z>
[*
\	<F> *
]	<D> *
^	<Shift><S>
_	<Shift><X>
`	N/A
a	<Alpha><A>
b	<Alpha>
c	<Alpha><C>
d	<Alpha><D>
e	<Alpha><E>
f	<Alpha><F>
g	<Alpha><G>
h	<Alpha><H>
I	<Alpha><I>
j	<Alpha><J>
k	<Alpha><K>
l	<Alpha><L>
m	<Alpha><M>
n	<Alpha><N>
o	<Alpha><O>
p	<Alpha><P>
q	<Alpha><Q>
r	<Alpha><R>
s	<Alpha><S>
t	<Alpha><T>
u	<Alpha><U>
v	<Alpha><V>
w	<Alpha><W>
x	<Alpha><X>
y	<Alpha><Y>
z	<Alpha><Z>
{	<Shift>
	<Shift><F>
}	<Shift><D>
~	N/A

* Alpha Mode