

VT/HP Keyboard Map

for External Keyboard VRC 8900

Booting Procedures

Boot Type	Procedure
Suspend	Hold Power for 1-2 seconds
Warm Boot	Hold Power for 5-8 seconds
Cold Boot	Hold Power for 8-12 seconds

Local Terminal Functions

Local Function	Key Sequence
Program Information	<Alt><P>
Keyclicks On/Off	<Alt><K>
Quiet Mode	<Alt><Q>
Terminal Configuration	<Alt><C>
Host Configuration	<Alt><R>
VT/HP Terminal Setup	N/A
Close Session	<Alt><T>
Previous Session	<Shift>< ← >
Next Session	<Shift>< → >
Caps Lock	N/A
View Mode On/Off	<Alt><Z>
Scroll Left	<Left Arrow>
Scroll Right	<Right Arrow>
Scroll Up	<Up Arrow>
Scroll Down	<Down Arrow>

VT/HP Keyboard Map

for External Keyboard VRC 8900

VT-100 Emulation Keys

VT-100 Key	Key Sequence
Return	<Enter>
Backspace	<BkSp>
Tab	<Tab>
Up Arrow	<Up>
Left Arrow	<Left>
ESC	<Esc>
BS	<BkSp>
LF	<Ctrl><Enter>
Hard Terminal Reset	<Alt><H>

VT-100 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	<Ctrl><BkSp>
Backtab	<Shift><Tab>
Down Arrow	<Down>
Right Arrow	<Right>
PF1	<F1>
PF2	<F2>
PF3	<F3>
PF4	<F4>

VT-220 Emulation Keys

VT-220 Key	Key Sequence
Return	<Enter>
Backspace	<BkSp>
Tab	<Tab>
Up Arrow	<Up>
Left Arrow	<Left>
Hard Terminal Reset	<Alt><H>
Find	<Shift><Esc>
Insert Here	<Shift>
Prev Screen	<Shift><Up>
PF1	<F1>
PF2	<F2>
PF3	<F3>
PF4	<F4>
BREAK ¹	N/A
F6	<F6>
F7	<F7>
F8	<F8>
F9	<F9>
F10	<F10>

VT-220 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	<Ctrl><BkSp>
Backtab	<Shift><Tab>
Down Arrow	<Down>
Right Arrow	<Right>
Soft Terminal Reset	<Alt><S>
Select	<Ctrl><Esc>
Remove	
Next Screen	<Shift><Down>
F11	<Shift><F1>
F12	<Shift><F2>
F13	<Shift><F3>
F14	<Shift><F4>
F15/Help	<Shift><F5>
F16/Do	<Shift><F6>
F17	<Shift><F7>
F18	<Shift><F8>
F19	<Shift><F9>
F20	<Shift><F10>

¹ The BREAK key is currently not available.

VT/HP Keyboard Map

for External Keyboard VRC 8900

HP Emulation Keys²

HP Key	Key Sequence
Return	<Enter>
Backspace	<BkSp>
Tab	<Tab>
Up Arrow	<Up>
Left Arrow	<Left>
Insert Line	<Shift>
Insert Char	
Hard Terminal Reset	<Alt><H>
Prev	<Shift><Up>
Clear Line	<Shift><F3>
Insert Char with wrap	<Shift><F5>
Scroll Down	<Shift><F7>
F1	<F1>
F2	<F2>
F3	<F3>
F4	<F4>
User Key Menu	<F10>

HP Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	<Ctrl><BkSp>
Backtab	<Shift><Tab>
Down Arrow	<Down>
Right Arrow	<Right>
Delete Line	<Shift><Esc>
Delete Char	<Ctrl><Esc>
Soft Terminal Reset	<Alt><S>
Next	<Shift><Down>
Clear Display	<Shift><F4>
Delete Char with wrap	<Shift><F6>
Scroll Up	<Shift><F8>
F5	<F5>
F6	<F6>
F7	<F7>
F8	<F8>
System Modes Menu	<Shift><F10>

² The BREAK and STOP keys are currently not available.

VT/HP Keyboard Map

for External Keyboard VRC 8900

VT/HP Character Map

Char	Key Sequence
^@	<Ctrl><2>
^A	<Ctrl><A>
^B	<Ctrl>
^C	<Ctrl><C>
^D	<Ctrl><D>
^E	<Ctrl><E>
^F	<Ctrl><F>
^G	<Ctrl><G>
^H	<Ctrl><H>
^I	<Ctrl><I>
^J	<Ctrl><J>
^K	<Ctrl><K>
^L	<Ctrl><L>
^M	<Ctrl><M>
^N	<Ctrl><N>
^O	<Ctrl><O>
^P	<Ctrl><P>
^Q	<Ctrl><Q>
^R	<Ctrl><R>
^S	<Ctrl><S>
^T	<Ctrl><T>
^U	<Ctrl><U>
^V	<Ctrl><V>
^W	<Ctrl><W>
^X	<Ctrl><X>
^Y	<Ctrl><Y>
^Z	<Ctrl><Z>
ESC	<Esc>
^\ <_>	<Alt><F7>
^J <_>	<Alt><F8>
^^ <_>	<Alt><F9>
^_ <_>	<Alt><F10>
Space	<Space>
!	<Alt><2>
“	<Ctrl><5>
#	<Shift><2>
\$	<Alt><3>
%	<Alt><4>
&	<Alt><1>
'	<Ctrl><4>
(	<Shift><4>
)	<Shift><5>
*	<Shift><1>

Char	Key Sequence
+	<Shift><7>
,	<Alt><0>
-	<Shift><8>
.	<Shift><9>
/	<Shift><0>
0	<0>
1	<1>
2	<2>
3	<3>
4	<4>
5	<5>
6	<6>
7	<7>
8	<8>
9	<9>
:	<Shift><6>
;	<Ctrl><6>
<	<Alt><7>
=	<Alt><6>
>	<Alt><8>
?	<Shift><3>
@	<Ctrl><7>
A	<Shift><A>
B	<Shift>
C	<Shift><C>
D	<Shift><D>
E	<Shift><E>
F	<Shift><F>
G	<Shift><G>
H	<Shift><H>
I	<Shift><I>
J	<Shift><J>
K	<Shift><K>
L	<Shift><L>
M	<Shift><M>
N	<Shift><N>
O	<Shift><O>
P	<Shift><P>
Q	<Shift><Q>
R	<Shift><R>
S	<Shift><S>
T	<Shift><T>
U	<Shift><U>

Char	Key Sequence
V	<Shift><V>
W	<Shift><W>
X	<Shift><X>
Y	<Shift><Y>
Z	<Shift><Z>
[	<Ctrl><8>
\	<Alt><9>
]	<Ctrl><9>
^	<Alt><5>
_	<Ctrl><0>
`	<Ctrl><F6>
a	<A>
b	
c	<C>
d	<D>
e	<E>
f	<F>
g	<G>
h	<H>
I	<I>
j	<J>
k	<K>
l	<L>
m	<M>
n	<N>
o	<O>
p	<P>
q	<Q>
r	<R>
s	<S>
t	<T>
u	<U>
v	<V>
w	<W>
x	<X>
y	<Y>
z	<Z>
{	<Alt><A>
	<Ctrl><F5>
}	<Alt>
~	<Ctrl><F7>